



2016 KXM MARINE AMPLIFIERS



KXWRC

Made For Your Boat

- Superior Sound Quality and Raw Power
- Small Footprint
- Aluminum Chassis
- Covered and Gasketed Controls For Superior Weather Protection
- Conformal Coated Circuit Boards
- ABYC/NMMA-Compliant Power Connections
- Stainless-Steel Hardware Included

Full Of Technology

- KICKEQ+™ 18dB Variable Bass Boost
- Lighted Gain Knobs With Clip Indicator
- DSP-Controlled Preamplifier
- Works With Any Radio, Thanks to FIT2™ (Fail-Safe Integration Technology)
- Class-D Power

KXMA 800.5/1200.1 Amps With Sub Channel

- KXMA1200.1 and KXMA800.5 Bass Output Now 1-Ohm Stable
- Bluetooth® Wireless Remote Included
- SHOCwave™ Bass-Restoration Processing
- Clipping Indicator
- Bass-Boost Control
- Gain Control

FOR MORE INFO: www.kicker.com/kxm-amplifiers





2016 KXM MARINE AMPLIFIERS

MODEL: KXMA	1200.1	1200.2	400.2	400.4
Power (watts/ch) 4 Ohm Stereo:	-	300x2	100x2	50x4
Power (watts/ch) 2 Ohm Stereo:	-	600x2	200x2	100x4
Power (watts/ch) 4 Ohm Mono Bridged:	-	-	400x1	200x2
Power (watts/ch) 4 Ohm Mono Sub Ch:	600x1	-	-	-
Power (watts/ch) 2 Ohm Mono Sub Ch:	1200x1	-	-	-
1 Ohm Stable Mono Sub Ch:	YES	-	-	-
SHOCwave Processing:	YES	-	-	-
Bluetooth Remote Control:	YES	-	-	-
Length (in./cm) :	9-9/16, 24.4	11-3/16, 28.4	9-9/16, 24.4	11-3/16, 28.4
All Models H: 2-1/8, 5.5 W: 8-5/16, 21				
Frequency Response (Hz):	10Hz-160Hz	10Hz-20kHz	10Hz-20kHz	10Hz-20kHz
Input Sensitivity All Models: 250mV-10V				
Signal to Noise Ratio All Models: 95dB				
Subsonic Filter (KXMA1200.1): Variable 10-80Hz, 24/dB Octave				
Crossover (Mono): Variable LP 40Hz-160Hz, 24dB/octave				
Crossover (2ch): OFF/HP/BP, Variable 40-500Hz & 400-5,000Hz w/10X Switch, 24dB/Octave				
Crossover (4ch):				

Amp 1: OFF/HP/LP; Variable 10-5,000Hz with X10 switch

Amp 2: OFF/HP/LP/BP; Variable HP, 10-500Hz; Variable LP, 40-5,000Hz with 10X Switch Slope: 24dB/octave

KickEQ+™ Bass Boost (2/4ch): Variable 0-18dB @40Hz

KickEQ+™ Bass Boost (Mono): Variable 0-18dB @20-80Hz (Adjustable)

MODEL: KXMA	800.8	800.5
Power (watts/ch) 4 Ohm Stereo:	50x8	50x4
Power (watts/ch) 2 Ohm Stereo:	100x8	100x4
Power (watts/ch) 4 Ohm Mono:	200x4	200x2
Power (watts/ch) 4 Ohm Mono Sub Ch.:	-	200x1
Power (watts/ch) 2 Ohm Mono Sub Ch.:	-	400x1
1 Ohm Stable Mono Sub Ch:	-	YES
SHOCwave Processing:	-	YES
Bluetooth Remote Control:	-	YES
Bluetooth Range:	-	TBD
Length (in./cm):	14-3/4, 37.4	12-3/4, 32.4

All Models H: 2-1/8, 5.5 W: 8-5/16, 21

Frequency Response (Hz): 10Hz-20kHz Amps 1/2: 10Hz-20kHz

Frequency Response (Hz) (5ch.) Sub Amp: 10Hz-160Hz

Input Sensitivity: 250mV-10V

Signal to Noise Ratio: 95dB

Subsonic Filter: - Variable 10-80Hz 24/dB Octave

Crossover (5ch): AMP 1: OFF/HP/LP, Variable 10-500Hz w/10X Switch, 24dB/Octave

AMP 2: OFF/HP/LP/BP, Variable HP 10-500Hz, Variable LP 40-5,000Hz w/10X Switch, 24dB/Octave

SUB: Variable LP 40-160Hz; 24dB/Octave

Crossover (8ch) Amp 1/2: OFF/HP/LP; Variable 10-5,000Hz with X10 switch

Amp 3/4: OFF/HP/LP/BP; Variable HP, 10-500Hz; Variable LP, 40-5,000Hz with 10X switch Slope: 24dB/Octave

KickEQ+™ Bass Boost (8ch): Variable 0-18dB @40Hz

KickEQ+™ Bass Boost (5ch): Variable 0-18dB @20-80Hz (Adjustable)



FOR MORE INFO: www.kicker.com/kxm-amplifiers