

KICKER

KEY500.1 SMART MONO AMPLIFIER/PROCESSOR

NEW!
20
07



WHAT MAKES IT SUPERIOR?

- AI-Driven DSP – One-Step, Automatic Calibration that Dramatically Improves Audio Quality
- Compatible with Start/Stop Vehicle Technology
- FIT2 Technology Allows It to Work with Nearly Any Radio

Model	KEY500.1
RMS power [watts/channel] @ 14.4V:	
1 Ohm mono:	500x1
2 Ohm mono:	300x1
4 Ohm mono:	150x1
Frequency Response:	10-160Hz, +0/-1dB
Signal-to-Noise Ratio:	>90dB, α-weighted, re: rated power
Input Sensitivity:	Low level 125mV-5V, High level 1V-40V
Active Crossover:	24dB/octave, variable LP 40-160Hz, variable HP 10-40Hz
KickEQ+ Boost:	Variable 0-6dB, centered @ 40Hz
Length [in, cm]:	8-1/8, 20.7
Height [in, cm]:	1-11/16, 4.3
Width [in, cm]:	4-1/8, 9.2

FOR MORE INFO : www.kicker.com

